




**SKYWOODS**  
-Lights conquer the outdoors-


**ELECTRIC**

**SPECIALE  
LOISIR**

SKU	Designation	French Law	Length (cm)	Width (cm)	Height (cm)	Weight (g)	Lumens	Battery	MSRP
A61232	Skywoods L53A1F	Vente libre	5.9	3.1	4.5	89	360	Rechargeable	86.00 € incl. tax

## Tactical Flashlight with Integrated Laser.

- LED: XF-S2 + laser
- Brightness: 360 Lumens
- Laser: green
- Battery: 1 integrated 122025/500mAh battery (rechargeable)
- Charging time: 3 hours
- Beam distance: High ? 130m
- Lux: high > 4400 Lux
- Charging method: Magnetic charging, with USB cable and magnetic connector
- Material: Aluminum alloy
- Water resistance: IP66
- Impact resistance: 1m
- Rail attachment width: 2-2.2cm
- Lighting modes: steady, strobe, laser, steady/strobe + laser
- Operating time: Steady: 2 hours, Strobe @ 10Hz: 3 hours, Steady + laser: 1 hour, Laser: 25 hours
- Dimensions: 59\*31\*45.4 mm
- Net weight: 89g (with battery)

### Continuous Light Output:

- The LED chip in this tactical light offers a maximum brightness of 360 lumens in continuous mode, ensuring reliable and constant lighting.

### **Adjustable and Precise Laser:**

- The integrated 532nm, <5mW laser is Class IIIA. The laser's elevation and orientation are adjustable using the Allen key included in the packaging, providing maximum precision.

### **Durable and Waterproof Construction:**

- Made from aircraft-grade anodized aluminum, this device is shock and vibration resistant, and is waterproof to IP66 standards, ensuring optimal durability even in harsh conditions.

### **Rechargeable Battery and Battery Life:**

- The built-in 500mAh battery provides up to 2 hours of continuous operation at 650 lumens. Recharging is convenient via the magnetic charging port, with the cable included in the package.

### **Charge Indicator:**

- The charging indicator, located near the magnetic charging port, displays in red during charging and in green once the battery is fully charged, providing clear visibility of the battery status.

### **Intuitive Use:**

- The laser switch turns the laser on and off. A single press activates/deactivates regular mode, while a two-second press activates strobe mode. In strobe mode, a two-second press completely deactivates the strobe function, ensuring precise and customized use.

*Les prix de vente conseillés sont mentionnés à titre indicatif. Les armuriers sont libres de vendre au prix qu'ils souhaitent. Textes et photos non contractuels, sujet à modification.*